

## Contents

---

1	<b>PLL2026A</b>	<b>30° x 80° FWHM</b>	Pag. 2
2	<b>PLL2026B</b>	<b>60° x 110° FWHM</b>	Pag. 3
3	<b>PLL2026C</b>	<b>90° x 110° FWHM</b>	Pag. 4
4	<b>PLL2026D</b>	<b>35° FWHM Asymmetrical**</b>	Pag. 5
5	<b>PLL2026L</b>	<b>90° x 150° Asymmetrical</b>	Pag. 6
6	<b>PLL2026E*</b>	<b>30° x 80° FWHM</b>	Pag. 7
7	<b>PLL2026F*</b>	<b>60° x 110° FWHM</b>	Pag. 8
8	<b>PLL2026G*</b>	<b>90° x 110° FWHM</b>	Pag. 9
9	<b>PLL2026H*</b>	<b>35° FWHM Asymmetrical**</b>	Pag. 10
10	<b>ASSEMBLY SPECIFICATION</b>		Pag. 11
11	<b>Materials / Use and Maintenance / Disclaimer</b>		Pag. 12

---

## NOTE

\* Designed to **comply with Zhaga - Book 7 standards**

\*\* Max Candela @ 5°



The part numbers ending “A” to “D” and “L”, have 38.7 mm pitch between the mounting fins; fit for PCB with 24.0mm maximum width.

**Designed to comply with Zhaga standards.**


The part numbers ending “E” to “H” have 54.0 mm pitch between the mounting fins; fit for PCB with 40.0mm maximum width.

**Designed to comply with Zhaga - Book 7 - standards.**

## PLL2026A - 30° FWHM





- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 30°
- Full angle C0-C180 at 10% from maximum: ~ 60°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip






## PLL2026C - 90° FWHM




- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 90°
- Full angle C0-C180 at 10% from maximum: ~ 130°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip




Project and Design owned by Khatod OPTOELECTRONIC s. r. l.  
The technical solutions adopted in this design are Khatod intellectual property, they cannot be reproduced and transmitted to third parties without our prior written permission. Unauthorized disclosure of confidential proprietary information will be prosecuted by law.

DESCRIPTION : <b>LINEAR LENS</b>	DESIGNER : <b>LM/DP</b>	PROJECT : <b>PLL 2026 AX</b>
CODE : <b>PLL 2026 C</b>	CHECKED : <b>SB/GV</b>	DATE : <b>02/02/2017</b>
<b>KHATOD</b> Via Alessandro, 28 Cusano Milanese Milano ITALIA WWW.KHATOD.COM	All Dimensions in mm General Tolerances +/-0.25	MATERIAL : <b>PMMA GN</b>
SCALE : <b>1 : 1</b>		SHEET : <b>1 of 1</b>




## PLL2026D - Asymmetrical Beam




- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 35°
- Full angle C0-C180 at 10% from maximum: ~ 60°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip





## PLL2026L - Asymmetrical Beam




- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 145°
- Full angle C0-C180 at 10% from maximum: ~ 90°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip





## PLL2026E - 30°FWHM - Designed to comply with Zhaga Book 7




- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 30°
- Full angle C0-C180 at 10% from maximum: ~ 60°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip



## PLL2026F - 60° FWHM - Designed to comply with Zhaga Book 7






- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 60°
- Full angle C0-C180 at 10% from maximum: ~ 85°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip








## PLL2026G - 90° FWHM - Designed to comply with Zhaga Book 7




- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 90°
- Full angle C0-C180 at 10% from maximum: ~ 130°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip




## PLL2026H - Asymmetrical Beam - Designed to comply with Zhaga Book 7



- Material = PMMA Clear
- Full angle C0-C180 at 50% from maximum: ~ 35°
- Full angle C0-C180 at 10% from maximum: ~ 60°
- The light spots here represented refer to tests carried out with 22 ½ Watt LEDs, 5.6x3mm size, ~ 1100lm@Strip



## Assembly Specification




Example:

Assembly using common Strip LEDs

Maximum width: 24.0 mm

- Use TCEI M3 screws
- Use Press Fit
- Maximum tightening torque: 0.48 Kn






Example:

Assembly using Strip LEDs complying with Zhaga Book 7

Maximum width: 40.0 mm

- Use TCEI M3 screws
- Use Press Fit
- Maximum tightening torque: 0.48 Kn



## Materials

<b>Material</b>	<b>Top</b>
PMMA 8N	-40°.....90°C
<b>For further information please visit Evonik website</b>	

## Notes:

- Intensity (I) and illuminance (E) data are normalized by 1000 lm
- The optical values shown are the result of optical simulations carried out with LIGHTTOOLS, ASAP and ZEMAX software systems. The optical simulations are carried out on the basis of the typical values provided in the LED manufacturers' official datasheets. The photometric analysis has been carried out on physical samples. On request, by supplying your PCB, we can provide the measurement photometric file.

## Use and Maintenance

- DO NOT HANDLE OR INSTALL LENSES WITHOUT WEARING GLOVES, SKIN OILS MAY DAMAGE LENS OR LIGHT TRANSMISSION;
- CLEAN LENSES WITH MILD SOAP AND WATER AND A SOFT CLOTH;
- DO NOT USE ANY COMMERCIAL CLEANING SOLVENTS ON LENSES.

## Disclaimer

Please note that flow lines and weld lines on the external surfaces of the lenses are acceptable if the optical performance of the lens is within the specifications.

Should you require further information, please contact Khatod for advice. All lens testing must be subject to identical conditions as Khatod test condition. Khatod Optoelectronic, Milan, Italy, manufactures lenses for LEDs. Any other use of the lens shall void our liability and warranty. The lenses are an inert component to be used in the manufacture of various products. Our warranty and liability are limited only to the manufacture of the lens. You may not modify, copy, distribute reproduce, license or alter the lens and related materials of Khatod. Khatod does not warrant against damages or defects arising out of the use or misuse of the products; against defects or damage arising from improper installation, or against defects in the product or in its components. No warranty of any kind, expressed or implied, is made regarding the safety of the products. The entire risk as to the quality or performance of the product is with the buyer. In no event shall Khatod be liable for any direct, indirect, punitive, incidental, special, consequential damages, or any damages whatsoever arising out of or connected with the use or misuse of the product. Khatod shall not have any obligation with respect to the product or any part thereof, whether based on contract, tort, strict liability or otherwise. Buyer assumes all risks and liability from use of the product. The laws of Milan, Italy govern this product warranty and liability and you hereby consent to the exclusive jurisdiction and venue of courts in Milan, Italy in all disputes arising out of or relating to the use of this product. Production, marketing, distribution, sale of these products as well as their possible modifications and variations are only exclusive right of Khatod Optoelectronic. No company can perform any of these actions without written permission released by Khatod Optoelectronic. The information contained in this document is proprietary of Khatod Optoelectronic and may change without notice.

REPRODUCTION PROHIBITED.